

## NOVA 10 CONNECT

03.6102C



Light control app



**//Powerbank**  
Built-in power bank  
with USB outlet to  
charge mobile devices

**3**  
years  
warranty\*



### JUST CONNECT

Add the connector matching  
your battery pack



**BOSCH**  
**BOSCH GREEN**  
**DEWALT**  
**EINHELL**  
**FEIN**  
**FESTOOL**  
**FLEX**  
**HAZET**  
**HIKOKI**  
**INGERSOLL**  
**MAKITA**  
**MILWAUKEE**  
**RIDGID**  
**SNAP-ON**  
**WÜRTH**



\*go to [scangrip.com](http://scangrip.com) to register



High efficiency  
COB LED



165 lm/W



10000 lm @ 100%  
7500 lm @ 75%  
5000 lm @ 50%  
2500 lm @ 25%  
1000 lm @ 10%



1600-16000  
lux @0.5m



Compatible with  
METABO / CAS  
battery system  
12V 4.0 Ah - 18V 5.2 Ah  
and 15 other 18V  
battery packs by using  
the SCANGRIP  
CONNECTOR



75W



0.5-5.5h@12V 4.0 Ah battery  
1.25-12h@18V 5.2 Ah battery  
Backup: 1h@1000 lm



-10° to +40° C



IK07



1m



IP65  
IP54 with battery cover



304x292x131 mm



3.72 kg



USB power bank:  
5VDC / 1A


# BATTERY, CHARGER, CONNECTORS AND POWER SUPPLY ARE SOLD SEPARATELY

## SCANGRIP CONNECTORS for 18V battery packs



BOSCH - 03.6140C  
BOSCH GREEN - 03.6141C  
DEWALT - 03.6142C  
EINHELL - 03.6143C  
FEIN - 03.6144C  
FESTOOL - 03.6153C  
FLEX - 03.6145C  
HAZET - 03.6146C  
HIKOKI - 03.6147C  
INGERSOLL - 03.6152C  
MAKITA - 03.6148C  
MILWAUKEE - 03.6149C  
RIDGID - 03.6154C  
SNAP-ON - 03.6151C  
WÜRTH - 03.6150C

## Accessories



POWER SUPPLY  
03.6123C



CAS BATTERY  
12V 4.0 Ah  
03.6120



CAS BATTERY  
18V 5.2 Ah  
03.6121



CAS CHARGER  
03.6122

# UK NOVA 10 CONNECT

WARNING - RISK OF FIRE:  
Minimum distance from lighted objects 0.1m

## WARNING:

- Always respect applicable legislation for working with electrical equipment in order to reduce the risk of accidents.
- Avoid looking directly into the beam of light, as this will result in dazzling.
- Do not use the lamp near a naked flame.
- Protect the mains cable from oil, heat and sharp edges.
- Internal backup battery must be replaced with an original SCANGRIP battery.
- Do not leave the battery flat, as this could render it INCAPABLE of being charged again.
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.
- Luminaire is only suitable for direct mounting on non-combustible surfaces.
- The luminaire is designed to work with all Metabo CAS battery packs.
- If the lamp is disconnected from mains and the battery is discharged, push the power button to enable internal back up battery. 10% LED will blink to indicate back up mode.

## THE PROCESS TO DELETE THE PIN CODE IS:

- Turn on the Bluetooth function.
- Press the Bluetooth button for 10 second.
- The pin code is reset.

## INTEGRATED BLUETOOTH LIGHT CONTROL:


- Turn lamp on/off or adjust lamp output.
- Connect, up to 4 lamps together.
- Assign a pincode to prevent other users from controlling the lamp.

Compliant with iOS 10.3 or higher and Android 5.0 or higher.

Go to iTunes App Store, Google Play or download the app from our website.

## USE:

- To turn the lamp on or off, press the A button.
- To increase the brightness, press the B button.
- To decrease the brightness, press the C button.
- When the brightness level is changed, the new value is saved, and the lamp will start at that level the next time it is turned on.
- To enable/disable Bluetooth, press the D button.



## THE LAMP HAS THREE DIFFERENT IP RATINGS DEPENDING ON THE USE:

- IP65 when used with a Scangrip power supply.
- IP54 When the battery cover is mounted and closed.
- IP30 When the battery cover is removed and using an external battery.

## BATTERY COMPLIANCE:

- The work light is designed to be used with Metabo CAS batteries.
- The lamp is also compatible with 3rd party 18V batteries by using the SCANGRIP CONNECT system.
- It will accept the following battery voltages; 12V and 18V.
- It is possible to use a Scangrip power supply instead of a battery.
- When using a Scangrip power supply the battery cover must be removed.

## USB POWER OUTLET:

- Built-in USB power outlet to charge mobile devices.
- Output: 5V, 1A
- The USB outlet is disabled when the lamp is in backup mode.



Discarded electrical products must not be disposed of together with household waste. Please use recycling facilities.

Ask your local authority or retailer for advice on recycling.

- The battery must be removed from the device before it is broken up

- The device must be disconnected from the mains when the battery is removed

- Please dispose of the battery safely