

INSTALLATION INSTRUCTIONS

HOLE CUT SIZE (TAILLE DE COUPE)

4"Round hole cut: ϕ 108mm 4 $\frac{1}{4}$ "

6"Round hole cut: ϕ 157mm 6 $\frac{3}{16}$ "

8"Round hole cut: ϕ 187mm 7 $\frac{3}{8}$ "

4"Square hole cut: 108mmx108mm 4 $\frac{1}{4}$ "

6"Square hole cut: 157mmx157mm 6 $\frac{3}{16}$ "

8"Square hole cut: 187mmx187mm 7 $\frac{3}{8}$ "

⚠ WARNING

RISK OF PERSONAL INJURY – PLEASE READ THESE INSTRUCTIONS CAREFULLY. FOLLOW ALL INSTALLATION INSTRUCTIONS AND OBSERVE ALL WARNINGS.

Make sure the "supply" voltage corresponds to the "rated" product voltage 120V 60Hz.

Retain these instructions. Note: If you are an installer, please give these instructions to the property owner for future reference.

Risk of injury: Always wear the necessary safety equipment to prevent injuries when opening, handling, installing and maintaining this product.

Risk of electrical shock: This product must be installed in accordance with the applicable installation code by a professional familiar with the construction and operation of the product. The professional should also be aware of, and understand the hazards involved with the installation of this product.

Risk of Fire: Always consult with a qualified electrician to ensure the correct branch circuit conductor is utilized. The minimum conductor rating requirement is 90°C (194°F) in order to be code compliant.

We assume no responsibility for claims arising out of improper or careless installation and handling of this product.

INSTALLATION GUIDE

IMPORTANT SAFETY

INFORMATION:

Please read all of the instructions below BEFORE installation.

- Make sure the "supply" voltage corresponds to the "rated" product voltage 120V 60Hz.
- If the product is damaged, DO NOT ATTEMPT INSTALLATION AND DO NOT USE!
- The product MUST be installed by a qualified electrician in accordance with The National Electrical Code and corresponding local codes.

INSTALLATION STEPS

1. Make sure the fixture is disconnected from the J-Box. Open it.
2. Connect the wires as shown in step #2. Use wire nuts to insure you have a proper connection. Close the J-Box when completed.
3. Insert the J-Box into the "cut hole", leaving the connection cable outside. Connect the fixture to the J-Box by inserting the cable and securing it with a cap as shown in step #3.
4. Push the spring loaded clips upwards and insert the fixture base into the mounting hole. Release the clips and the fixture will be "pulled" into place against the ceiling.
5. Once assembly is complete, turn the power on to ensure the fixture is operating properly.

