


Bluetooth Voice Remote User Manual

Model : 1Y0UN6

1. Product Overview

- Model: **1Y0UN6**
 - Functions: Bluetooth connection, voice control, infrared (IR) learning
 - Compatible with : Android TV and supported set-top boxes (STB)
 - Power: 2 × AA batteries
-

2. Bluetooth Pairing

- Turn on Bluetooth on your host device (TV or STB).
 - Press and hold **OK** +  keys together until the indicator flashes once and then turns off. After ~3 seconds, the indicator will blink slowly. This means pairing mode is active.
 - On the host device, go to **Bluetooth Settings** → **Search Device and pair with Formuler remote**.
 - If pairing is successful, the indicator stays on for 2 seconds, then turns off.
 - If pairing fails, the remote will exit pairing mode automatically after ~60 seconds. Repeat steps above if needed.
-

3. Power & Battery

- Uses 2 × AA batteries.
 - Low battery indicator: Red light blinks quickly for 3 seconds.
 - If voltage is too low, the remote may stop working until batteries are replaced.
-

4. Power-Saving Features

- Enters **sleep mode** automatically after 10 seconds of no use.
 - Exits sleep mode when any key is pressed.
 - Voice control mode remains available.
-

5. Indicator Light Behavior

- **Voice mode active:** Red light stays on.
 - **Low battery:** Red light blinks quickly.
 - **Pairing mode:** Red light blinks slowly (searching) or quickly (connecting).
-

6. IR Learning Function

- Press and hold TV button for 5 seconds on Formuler remote
 - The LED goes from blinking to solid as your Formuler remote enters Learning Mode
- Press the button to be programmed on Formuler remote. When LED begins blinking slowly, the button is ready to be programmed
- Aim both remote's heads toward each other (distance less than 3cm) and press the button to be transferred on the TV remote

- If it is programmed correctly, Formuler remote's LED will blink 3 times
 - You may repeat steps 1-3 for other keys
 - Exit Learning Mode by pressing any other button on your Formuler remote, LED will turn off
-

7. Exiting Modes

- Press any key to exit pairing/learning mode.
 - Device will exit automatically after ~10 seconds of no action.
-

8. FCC Warning Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

9. ISED Canada Compliance Information

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- This device may not cause interference.
 - This device must accept any interference, including interference that may cause undesired operation of the device.
-

9. Radiation Exposure Statement (English)

This equipment complies with Canada's radiation exposure limits set forth for an uncontrolled

environment. To maintain compliance with IC's RF Exposure guidelines, this device and its antenna(s) must not be co-located or operated in conjunction with any other antenna or transmitter.

10. **Déclaration de conformité ISED (Français)**

Cet appareil contient des transmetteur(s)/récepteur(s) exempts de licence conformes aux RSS exempts de licence d'Innovation, Sciences et Développement économique Canada. L'utilisation est soumise aux deux conditions suivantes :

- Cet appareil ne doit pas provoquer d'interférences.
 - Cet appareil doit accepter toute interférence, y compris celles pouvant provoquer un fonctionnement indésirable.
-

11. **Exposition aux rayonnements (Français)**

Cet équipement est conforme aux limites d'exposition aux radiations établies pour un environnement non contrôlé. Pour maintenir la conformité aux directives d'exposition RF d'IC, cet appareil et ses antennes ne doivent pas être situés ou utilisés en conjonction avec une autre antenne ou un autre émetteur.